



Sorin Enache, Aurel Campeanu, Ion Vlad, Monica-Adela Enache

## Influence of Starting Cage Material upon Dynamic Behaviour of Reluctance Synchronous Motors

In this paper there is studied the dynamic regime behaviour of a reluctance synchronous motor fitted out with a starting cage. There are analyzed two concrete situations: cage made of aluminium and cage made of copper. There are presented the mathematical model of the motor, the simulation program and the simulations carried out for the two situations. For the case of cage made of aluminium there have been performed experimental tests for direct-on-line no-load starting, tests that confirm the simulations carried out. The paper ends with conclusions regarding the influence of the cage material upon the time-dependent variation of the main electrical and mechanical quantities of the motor.

Keywords: reluctance synchronous motor, mathematical model, simulations, experimental tests

### 1. Introduction

Dynamic regime behaviour of reluctance synchronous motors is a present problem, fact confirmed by several papers published in different international scientific manifestations [4], [5], [6], [7] etc.

The starting of these motors is, in the most cases, a direct-on-line one. This starting is possible owing to a short-circuited cage assembled on the rotor.

This paper aims at analyzing the dynamic regime mentioned before from the view point of the material which the starting cage is made of.

There will be considered two concrete situations: cage made of aluminium, respectively of copper.

## 2. Simulations

Using the mathematical model of reluctance synchronous motor detailed in [2] and the Matlab-Simulink program, presented in [3], there have been obtained the graphics from figures 1-11.

There are presented two categories of characteristics corresponding to the two types of cages (a – cage made of aluminium, b – cage made of copper).

In order to carry out this analysis, there has been assessed a reluctance synchronous motor having a cage made of aluminium and the following parameters:  $R_s = 3,77 \Omega$ ;  $R_D = 1,5 \Omega$ ;  $R_Q = 4,5 \Omega$ ;  $L_{s\sigma} = 0,0081 \text{ H}$ ;  $L_{D\sigma} = 0,0059 \text{ H}$ ;  $L_{Q\sigma} = 0,0067 \text{ H}$ ;  $L_d = 0,281 \text{ H}$ ;  $L_q = 0,081 \text{ H}$ ;  $J = 0,005 \text{ kgm}^2$ ;  $p = 2$ . The motor is supplied by a phase voltage of 220 V and operates in rated load ( $M_r = 7,6 \text{ Nm}$ ).

For the case of cage made of copper it has been considered that the cage geometrical dimensions are the same. As a consequence, the rotor resistances are the only values which are modified. The new values for which simulations have been carried out are:  $R_D = 1,05 \Omega$  and  $R_Q = 2,6 \Omega$ .




Figure 1. Characteristics  $i_A = f(t)$  for: a – cage made of aluminium, b - copper.






Figure 2. Characteristics  $i_d = f(t)$  obtained for the case of asynchronous starting.




a)




b)

Figure 3. Characteristics  $i_q=f(t)$ .




a)




b)

Figure 4. Characteristics  $i_s=f(t)$  corresponding to the two cases.



a)



b)

Figure 5. Characteristics  $i_D=f(t)$  corresponding to the two cases.




Figure 6. Characteristics  $i_0=f(t)$  obtained for the case of asynchronous starting.




Figure 7. Dependences  $\Psi_{md}=f(\Psi_{mq})$ .






Figure 8. Characteristics  $\Psi_m=f(t)$  corresponding to the two cases.




a)




b)

Figure 9. Characteristics  $m=f(t)$  obtained for the case of asynchronous starting.




a)




b)

Figure 10. Characteristics  $\Omega=f(t)$  corresponding to the two cases.



a)



b)

Figure 11. Characteristics  $\Omega=f(m)$ .

### 3. Experimental results

In order to carry out experimental tests there has been used the scheme presented in figure 12.




Figure 12. Block scheme of the experimental circuit.

The notations used are:

KPCI 3102 – data acquisition board [8];

STA 16 – connections block;

PII 200 – current transformer;

SS – speed sensor;

RSM – reluctance synchronous motor rated at 1,5 kW (starting cage made of aluminium).




Figure 13. Characteristics of the experimental current (1) and simulated (2).




Figure 14. Characteristics of the experimental speed (1) and simulated (2).

With the help of the experimental circuit has been monitored the no-load starting in case of direct-on-line starting. The time-dependent evolutions of the A phase current (Figure 13) and of the speed (Figure 14) is presented in comparison with its evolution obtained by simulation.

As it may be noticed, the two characteristics (experimental and simulated) are almost overlapped (little differences concerning the maximal currents are caused by the magnetic saturation phenomenon of the core).

In conclusion, the figures 13 and 14 confirm the simulations carried out (for the cage made of aluminium).

The experimental confirmation for the case of the copper cage is not necessary. The purpose of the paper is to assess the behaviour of such a motor before building it practically and to answer the question: "Is it worth or not to build such a motor?".

#### 4. Conclusions

The following conclusions emerge from the analysis of the figures 1-11:

- the duration of the currents transient regimes increases in case of cage made of copper (Figure 1-Figure 6);
- the magnetic flux modifies in larger limits in case of cage made of aluminium (Figure 8);
- the maximum torque obtained in case of cage made of aluminium is with approximately 15 Nm higher than the maximum torque obtained in case of cage made of copper (Figure 9);
- in case of cage made of aluminium the speed has higher transient values than in case of cage made of copper (Figure 10).

#### Acknowledgment

This work was partially supported by the grant number 30C/27.01.2014, awarded in the internal grant competition of the University of Craiova [1].

## References

- [1] Enache M.A., Contributions regarding monitoring of dynamic regimes of reluctance synchronous motors, Grant no. 30C/27.01.2014, University of Craiova.
- [2] Enache S., Campeanu A., Vlad I., Enache M.A., Aspects Regarding Dynamic Regimes Modelling, Simulation and Monitoring for Reluctance Synchronous Motors. OPTIM 10, Brasov, May 2010, Romania, 273–278.
- [3] Enache S., Campeanu A., Vlad I., Enache M.A., Supply Voltage and Resistant torque Influence on dynamic Characteristic of Reluctance Synchronous Motors, Annals of the University of Craiova, Series Electrical Engineering, Year 37, No. 37, 2013, 128-134.
- [4] Hendershot J.R., Miller T.J.E., Staton D.A., Lagerquist R., The Synchronous Reluctance Motor for Motion Control Applications. 21st Annual Symposium on Incremental Motion Control Systems and Devices, San Jose, California, June 15-19, 1992.
- [5] Hertel L., Hofmann W., Theory and Test Results of a High Speed Bearingless Reluctance Machine. Proceedings of PCIM 1999, Nuremberg, 1999, 143-147.
- [6] Honsinger V.B., Steady-State Performance of Reluctance Machines. IEEE Transaction on Power Apparatus and Systems, vol. PAS-90, no. 1, 1991, 305-317.
- [7] Spunei E., Piroi I., Comparative analysis between stationary and dynamic parameters of a synchronous generator with the main variable of the air gap magnetic induction. 2012 International Conference on Applied and Theoretical Electricity, 25-27 Oct. 2012, Craiova, Romania, 1-4.
- [8] \*\*\*\*\* KPCI 3100 Series, Users Manual, Keithley Metrabyte, 2010.

### Addresses:

- Prof. Dr. Eng. Sorin Enache, University of Craiova, Faculty of Electrical Engineering, 107 Decebal Street, 200440, Craiova, [senache@em.ucv.ro](mailto:senache@em.ucv.ro)
- Prof. Dr. Eng. Aurel Campeanu, University of Craiova, Faculty of Electrical Engineering, 107 Decebal Street, 200440, Craiova, [acampeanu@em.ucv.ro](mailto:acampeanu@em.ucv.ro)
- Prof. Dr. Eng. Ion Vlad, University of Craiova, Faculty of Electrical Engineering, 107 Decebal Street, 200440, Craiova, [ivlad@em.ucv.ro](mailto:ivlad@em.ucv.ro)
- Lect. Dr. Eng. Monica-Adela Enache, University of Craiova, Faculty of Electrical Engineering, 107 Decebal Street, 200440, Craiova, [menache@em.ucv.ro](mailto:menache@em.ucv.ro)